

Alternate Carrier Cheat Sheet

Explanation of Fields

Access Point Settings

Name	Identifies the Access Point
APN	Carrier Specific (obtained from carrier)
Authenticate (NONE PAP CHAP)	
Username	
Password	

Connection Settings

Name	Identifies the Access Point
Homepage	Can be any website of your choice
Server Address	Carrier Specific (obtained from carrier)
Proxy (On Off)	
Proxy Address	
Proxy Port	
APN	

Optus Settings:

	Internet	MMS
Access Point		
Name	Optus Internet	Optus MMS
APN	yesinternet	mms
Authenticate	NONE	NONE
Username	<not set>	<not set>
Password	<not set>	<not set>
Connection		
Name	Optus Internet	Optus MMS
Homepage	<not set>	<not set>
Server Address	<not set>	http://mmsc.optus.com.au:8002/
Proxy	Off	On
Proxy Address	<not set>	61.88.190.10
Proxy Port	<not set>	8070
APN	Optus Internet	Optus MMS

Telstra Settings:

	Telstra - Internet	Telstra - MMS
Access Point		
Name	Telstra Internet	Telstra MMS
APN	Telstra.wap	Telstra.mms
Authenticate	NONE	NONE
Username	<not set>	<not set>
Password	<not set>	<not set>
Connection		
Name	Telstra Internet	Telstra MMS
Homepage	http://wap.telstra.com/wap	<not set>
Server Address	<blank>	http://mmsc.telstra.com:8002
Proxy	On	On
Proxy Address	10.1.1.181	10.1.1.180
Proxy Port	80	80
APN	Telstra Internet	Telstra MMS

(3) Settings:

	(3) - Internet	(3) - MMS
Access Point		
Name	3 Services	3MMS
APN	3services	mms
Authenticate	NONE	NONE
Username	<not set>	<not set>
Password	<not set>	<not set>
Connection		
Name	3 Services	3MMS
Homepage	<not set>	<not set>
Server Address	<not set>	http://mmsc.three.net.au:10021/mmsc
Proxy	Off	On
Proxy Address	<not set>	10.176.57.25
Proxy Port	<not set>	8799
APN	3 Services	3MMS

Vodafone Settings:

Fields	Vodafone - Internet	Vodafone - MMS
Access Point		
Name	VF WEB	VF PXT
APN	live.vodafone.com	ive.vodafone.com
Authenticate	PAP	PAP
Username	<not set>	<not set>
Password	<not set>	<not set>
Connection		
Name	VF WEB	VF PXT
Homepage	http://live.vodafone.com	<not set>
Server Address	<not set>	http://pxt.vodafone.net.au/pxtsend
Proxy (On Off)	Off	On
Proxy Address	<not set>	10.202.2.06
Proxy Port	<not set>	8080
APN	VF WEB	VF PXT

TPG Settings:

Fields	TPG Mobile - Internet	TPG Mobile - MMS
Access Point		
Name	Optus Internet	Optus MMS
APN	yesinternet	mms
Authenticate	CHAP	CHAP
Username	<not set>	<not set>
Password	<not set>	<not set>
Connection		
Name	Optus Internet	Optus MMS
Homepage	<not set>	<not set>
Server Address	<not set>	http://mmsc.optus.com.au:8002/
Proxy (On Off)	Off	On
Proxy Address	<not set>	61.88.190.10
Proxy Port	<not set>	8070
APN	Optus Internet	Optus MMS

Crazy John's Settings:

Fields	Crazy John's - Internet	Crazy John's - MMS
Access Point		
Name	Crazy NET	Crazy MMS
APN	purtona.net	purtona.wap
Authenticate	NONE	NONE
Username	<not set>	<not set>
Password	<not set>	<not set>
Connection		
Name	Crazy NET	Crazy MMS
Homepage	<not set>	<not set>
Server Address	<not set>	http://purtona.mms/mmssend
Proxy (On Off)	Off	On
Proxy Address	<not set>	10.202.2.02
Proxy Port	<not set>	8080
APN	Crazy NET	Crazy MMS

Amaysim:

Fields	amaysim – Internet	amaysim – MMS
Access Point		
Name	Amaysim	MMS
APN	preconnect	mms
Authenticate	CHAP	PAP
Username	<not set>	<not set>
Password	<not set>	<not set>
Connection		
Name	Amaysim	MMS
Homepage	<not set>	<not set>
Server Address	<not set>	http://mmsc.optus.com.au:8002/
Proxy (On Off)	Off	On
Proxy Address	<not set>	10.202.2.02
Proxy Port	<not set>	8070
APN	Amaysim	MMS

iinet Settings:

	Internet	MMS
Access Point		
Name	iinet Internet	Optus MMS
APN	internet	mms
Authenticate	CHAP	CHAP
Username	<not set>	<not set>
Password	<not set>	<not set>
Connection		
Name	iinet Internet	Optus MMS
Homepage	<not set>	<not set>
Server Address	<not set>	http://mmsc.optus.com.au:8002/
Proxy	Off	On
Proxy Address	<not set>	61.88.190.10
Proxy Port	<not set>	8070
APN	iinet Internet	Optus MMS

Dodo Settings:

Fields	Dodo - Internet	Dodo - MMS
Access Point		
Name	Internet	MMS
APN	Internet	mms
Authenticate	NONE	NONE
Username	<not set>	<not set>
Password	<not set>	<not set>
Connection		
Name	Internet	MMS
Homepage	<not set>	<not set>
Server Address	http://networker.optus.net.au/wap/index.wml	http://mmsc.optus.com.au:8002/
Proxy (On Off)	On	On
Proxy Address	202.139.83.152	61.88.190.10
Proxy Port	9201	9201
APN	default	mms

ALDI mobile Settings:

Fields	ALDI mobile - Internet	ALDI mobile - MMS
Access Point		
Name	Mobile Data	Mobile Data
APN	mdata.net.au	mdata.net.au
Authenticate	NONE	NONE
Username	<not set>	<not set>
Password	<not set>	<not set>
Connection		
Name	Mobile Data	Mobile Data
Homepage	<not set>	<not set>
Server Address	<not set>	http://mmsc.mdata.net.au:8003
Proxy (On Off)	Off	On
Proxy Address	<not set>	10.1.1.180
Proxy Port	<not set>	80
APN	default	mms